

# LGADs-based (outer) tracker for ECCE

- status of simulations in Fun4All


Wei Li (Rice University)



RICE

ECCE Tracking WG meeting  
May 21, 2021

# LGADs TOF simulation in Fun4All




- Silicon layers with timing and position smeared to expected resolution
- Timing and path length of each track stored for calculating the velocity
- Material budget is dummy for now but will update soon

Friederike Bock ([Friederike.Bock@cern.ch](mailto:Friederike.Bock@cern.ch)),  
Shuai Yang ([shuai.yang@rice.edu](mailto:shuai.yang@rice.edu))

[https://github.com/eic/fun4all\\_eicmacros/blob/master/common/G4\\_TTL\\_EIC.C](https://github.com/eic/fun4all_eicmacros/blob/master/common/G4_TTL_EIC.C)

	Default	$R_{\text{barrel}}$	Length	z location	$R_{\text{endcap,in}}$	$R_{\text{endcap,out}}$	$\eta$ coverage	Area (m <sup>2</sup> )
Backward	ETTL <sub>0</sub>			-1.555	0.077	0.632	[-3.7,-1.6]	1.23
	ETTL <sub>1</sub>			-1.585	0.078	0.62	[-3.7,-1.6]	1.19
Central	CTTL <sub>0</sub>	0.92	3.6				[-1.34,1.34]	20.8
	CTTL <sub>1</sub>	1.147	3.6				[-1.11,1.11]	25.9
Forward	FTTL <sub>0</sub>			2.87	0.116	1.527	[1.3,3.9]	7.28
	FTTL <sub>1</sub>			2.89	0.117	1.538	[1.3,3.9]	7.39
	FTTL <sub>2</sub>			3.4	0.138	2.185	[1.1,3.9]	14.94




# Position resolution


Pitch size: 1.3 mm – 700 (500)  $\mu\text{m}$   
(mainly limited by ASICs)

ETROC1 Single Pixel Layout


1.3mm x 1.3mm



LGADs consortium meeting on electronics:  
<https://indico.bnl.gov/event/11717/>



(a)






$\sigma_x$ : 20-30  $\mu\text{m}$   
for pitch of  $\sim 500 \mu\text{m}$

arXiv:2003.04838

Small pitch  $\rightarrow$  more channels ( $\sim 2 \text{ mW/ch}$ )  
 $\rightarrow$  more power consumption

# Material budgets

15%  $X_0$  for two layers, dominated by support (Al), electronics





Plan to implement 6mm thick Al for each layer in Fun4All

What is the impact on electron energy resolution?

# Forward tracking with LGADs

## Tracking w/o vs. w/ LGADs layers



LGADs layers will serve as both TOF and outer tracker (behind RICH) to improve  $p$  resolution by up to 50% at 100 GeV/c and efficiency at forward  $y$

# Backups




# PID performance

Forward ( $1 < \eta < 3.5$ ):


Central ( $|\eta| < 1$ ):

Backward ( $-3.5 < \eta < -1$ ):


$\sigma_t = 0$  ps




$\sigma_t = 20$  ps



0.2-4 GeV




0.2-2.5 GeV



0.2-3 GeV

all uncertainties ( $t_0$ ,  $t_f$ ,  $L$ ) included

# PID performance




Iterative procedure to determine  $T_0$ :

- Assume scattered e is detected by TOF
- Start with pion assuming for all other particles to fit  $T_0$
- Update mass assumption for outliers in next iterations

Details described in [https://wiki.bnl.gov/conferences/images/0/01/ERD29\\_progress\\_report\\_March2021.pdf](https://wiki.bnl.gov/conferences/images/0/01/ERD29_progress_report_March2021.pdf)  
(still optimizing)


# Concept of LGADs sensors

Precision position detectors:




e.g., silicon:  
**Thin & Light**  
**Segmented**  
**B tolerant**  
**Rad-hard**

Precision timing detector:



Scintillation  
Ionization  
+  
**High gain**

LGADs




Ultra Fast Silicon Detector E field

LGADs sensors:  
precision **position** and **timing**

# LGADs at the HL-LHC (2028)



## BTL: LYSO bars + SiPM readout:

- TK / ECAL interface:  $|\eta| < 1.45$
- Inner radius: 1148 mm (40 mm thick)
- Length:  $\pm 2.6$  m along z
- Surface  $\sim 38$  m<sup>2</sup>; 332k channels
- Fluence at  $4 \text{ ab}^{-1}$ :  $2 \times 10^{14} n_{\text{eq}}/\text{cm}^2$




## ETL: Si with internal gain (LGAD):

- On the CE nose:  $1.6 < |\eta| < 3.0$
- Radius:  $315 < R < 1200$  mm
- Position in z:  $\pm 3.0$  m (45 mm thick)
- Surface  $\sim 14$  m<sup>2</sup>;  $\sim 8.5$ M channels
- Fluence at  $4 \text{ ab}^{-1}$ : up to  $2 \times 10^{15} n_{\text{eq}}/\text{cm}^2$



CMS MTD

Endcap Timing Layer



$\sigma_T$ : 30-50 ps



Cost for ETL: \$10M for 15 m<sup>2</sup>  
(possible to optimize for low radiation)

## Particle ID in HI

CMS Phase-2 Simulation PbPb (5.5 TeV)

