

EIC FST Fun4All Simulation

Cheuk-Ping Wong
On Behalf of LANL EIC Team
Los Alamos National Laboratory
10-08-2020

Outline

- Motivation: summary table for the detector performance of the LANL FST design
- Parameters of the momentum and DCA resolutions
- Summary and Plan




Motivation

- Summary table for the detector performance of the LANL FST design
- To check whether the performance can meet the associated heavy flavor and jets physics requirements

Detector performance



physics requirements



arXiv:2009.02888



Simulation Setup

- Event configuration:
 - single (10) π^- per event for momentum (vertex) reconstruction
 - Vertex (0,0,0)
 - no smearing for vertex reconstruction
 - 20um smearing in x and y direction for track reconstruction
 - 7.5M events in each p_T bin
- Track configuration:
 - p_T : 1-30 GeV with varying increments
 - Pseudorapidity: 1-4 in lab frame
 - Hit efficiency at 95%
 - Pseudorapidity correction for ion beam angle


Latest FST Detector Setup

Design by Xuan

Plane	z (cm)	r_{in} (cm)	r_{out} (cm)	Pixel pitch (μm)	Silicon thickness (μm)
0	35	4	25	20	50
1	62.3	4.5	42	20	50
2	90	5.2	43	20	50
3	115	6	44	36.4	100
4	125	6.5	45	36.4	100
5	270	15	45	36.4	100



Momentum Resolution of FST with BeAST / Babar Magnet





Momentum Resolution Comparison

LBNL Silicon tracker + support structure

10um pixel pitch		$\delta p/p = Ap \oplus B$	
		A [%/GeV]	B [%]
$1.0 < \eta < 1.5$	B = 3.0T	0.016	0.427
	B=1.4T	0.035	0.921
$1.5 < \eta < 2.0$	B = 3.0T	0.012	0.462
	B=1.4T	0.026	0.997
$2.0 < \eta < 2.5$	B = 3.0T	0.018	0.719
	B=1.4T	0.041	1.548
$2.5 < \eta < 3.0$	B = 3.0T	0.039	1.336
	B=1.4T	0.088	2.830
$3.0 < \eta < 3.5$	B = 3.0T	0.103	2.428
	B=1.4T	0.217	5.234
$3.5 < \eta < 4.0$	B = 3.0T	0.295	4.552
	B=1.4T	0.610	9.797


LANL FST $\frac{\Delta p}{p}(p) = Ap + B$

η	B field	A (%/GeV)	B (%)
$1.0 \leq \eta < 1.5$	BeAST	0.023	0.499
	Babar	0.044	0.940
$1.5 \leq \eta < 2.0$	BeAST	0.009	0.420
	Babar	0.018	0.787
$2.0 \leq \eta < 2.5$	BeAST	0.016	0.630
	Babar	0.031	1.234
$2.5 \leq \eta < 3.0$	BeAST	0.015	1.120
	Babar	0.031	2.224
$3.0 \leq \eta < 3.5$	BeAST	0.025	1.630
	Babar	0.046	3.228
$3.5 \leq \eta < 4.0$	BeAST	0.026	1.855
	Babar	0.024	3.878




https://indico.bnl.gov/event/7913/contributions/41704/attachments/30564/47972/200924_Parametrizations.pdf

DCA_{2D} Resolution of FST with BeAST Magnet



- Issue with results using Babar magnet. Working with Jin to solve the problem
- These two fit functions represent the DCA resolution well especially at $\eta < 3$ and at high p_T

DCA_z Resolution of FST with BeAST Magnet



DCA Resolution Comparison

LBNL Silicon tracker + support structure
 10um pixel pitch

$$\sqrt{\left(\frac{A}{p_T}\right)^2 + B^2}$$

DCA _{2D}		A [$\mu\text{m GeV}$]	B [μm]
1.0 < η < 1.5	B = 3.0T	33.1	5.46
	B=1.4T	35.2	5.10
1.5 < η < 2.0	B = 3.0T	39.1	5.46
	B=1.4T	39.8	5.21
2.0 < η < 2.5	B = 3.0T	45.1	9.54
	B=1.4T	46.3	9.31

DCA _z		A [$\mu\text{m GeV}$]	B [μm]
1.0 < η < 1.5	B = 3.0T	55.9	5.89
	B=1.4T	56.2	5.41
1.5 < η < 2.0	B = 3.0T	108.2	8.74
	B=1.4T	106.3	8.36
2.0 < η < 2.5	B = 3.0T	207.3	19.77
	B=1.4T	201.8	21.50

LANL FST

Using BeAST Magnet $\frac{A}{p_T} + B$

η	DCA _{2D}	
	A ($\mu\text{m}\cdot\text{GeV}$)	B (μm)
1.0 ≤ η < 1.5	28.43	12.04
1.5 ≤ η < 2.0	37.97	6.38
2.0 ≤ η < 2.5	39.05	10.93
2.5 ≤ η < 3.0	46.88	16.99
3.0 ≤ η < 3.5	44.70	27.64


η	DCA _z	
	A ($\mu\text{m}\cdot\text{GeV}$)	B (μm)
1.0 ≤ η < 1.5	69.24	6.92
1.5 ≤ η < 2.0	116.60	6.64
2.0 ≤ η < 2.5	178.45	16.17
2.5 ≤ η < 3.0	342.90	41.67
3.0 ≤ η < 3.5	622.09	62.34

Summary

- Extracted detector performance parameters
- Different functions are tried in fitting the momentum and DCA resolutions. All these fit functions describe the resolution very well.

Plan

Momentum resolution using Pythia6 events



Detector simulation:


- Single track reconstruction performance with Pythia6 events
- Compare results to Geant single tracks events
- Running Pythia6 events with the integrated detector setup

Implement detector performance in heavy flavor jets study


- Heavy flavor and jets reconstruction

Back Up

DCA_r Resolution of FST with BeAST Magnet





DCA $_{\phi}$ Resolution of FST with BeAST Magnet



Integrated Detector Setup in Fun4All

FST Version 5 Parameters

Plane	z (cm)	r_{in} (cm)	r_{out} (cm)	Pixel pitch (μm)	Silicon thickness (μm)
0	35	4	25	20	50
1	62.3	4.5	42	20	50
2	90	5.2	43	20	50
3	115	6	44	36.4	100
4	125	6.5	45	36.4	100
5	270	15	45	36.4	100



Detector Design in Fun4all

Material sublayers of the plane detectors
(arbitrary scale)

