Photon Detector

XP85112

10µm MCP-PMT

53 mm Square, 8x8 Anode

- Superior Magnetic Field Immunity
- Enhanced Timing Performance


Applications

- Specialized Medical Imaging
- Cherenkov RICH, TOF, TOP, DIRC
- **High Energy Physics Detectors**
- ✓ Homeland Security

| Description | |
|--|--|
| Window options Photocathode Multiplier structure | Schott 8337B or equivalent, UVFS (-Q) Bialkali MCP chevron (2), 10 µm pore, 60:1 L:D ratio |
| Anode structure | 8×8 array, 5.9 / 6.5 mm (size / pitch) |
| Active area | 53×53 mm |
| Package open-area-ra | tio 80% |

| Photocathode characteristics | Min | Тур | Max | Unit |
|---|-----|-----|------|------|
| Spectral range: | 200 | | 650 | nm |
| Peak Quantum Efficiency at 380 nm* | | 22 | | % |
| Operating Characteristics | Min | Тур | Max | Unit |
| Overall Voltage for 10 ⁵ Gain * | | FIG | 2800 | V |
| Total anode dark current @ 10 ⁵ gain * | | 2 | 10 | nA |
| Spatial Uniformity | | 2:1 | | |
| Rise time** | | 0.5 | | ns |
| Pulse width** | | 0.7 | | ns |
| Transit time spread (σ_{tts})** | | 35 | 60 | ps |
| Maximum Magnetic Field Operation | | 2 | | Т |


Recommended Voltage Divider (not included)




CAUTION: POWER GROUND CONNECTION AND UNUSED ANODES MUST BE CONNECTED TO GROUND FOR SAFETY AND PROPER TUBE OPERATION

PLANACON®

Typical spectral response



Typical gain curve





^{*} Characteristic measured and recorded on the test ticket of each tube

Characteristic for single photoelectrons at 405 nm.


Photon Detector

XP85112


Outline (dimensions in mm)



Mass: ~128g



Internal Connection Schematic – XP85112/A1



| Min | Max | Unit |
|----------|------------|--|
| | 500 | V |
| | 2400 | V |
| | 500 | V |
| | 2800 | V |
| | 2 | μA |
| 0 -15 | +50 +50 | °C |
| | 0 -15 | 500 2400 500 2800 2 0 +50 |

^{*} Custom or unfurnished external connections are available upon request.

The information furnished is believed to be accurate and reliable, but is not guaranteed and is subject to change without notice. No liability is assumed by PHOTONIS USA Pennsylvania, Inc. for its use. Performance data represents typical characteristics and not specifications as actual, individual product performance may vary. Customers should verify that they have the most current product information before placing orders, and should independently test and evaluate PHOTONIS products for their intended use

No claims or warranties are made as to the application of PHOTONIS products or their suitability or fitness for any particular purpose. This document may not be reproduced, in whole or in part, without the prior written consent of PHOTONIS USA Pennsylvania, Inc.



^{**} Warning: Continuous operation at maximum ratings may result in shorter product life or unreliable performance.